

## AT9819 ACC

AT9819/TRI/SENS

PIR Sensor to suit AT9819/TRI

### Features

- Suits AT9819/TRI/30 & AT9819/TRI/50
- Relay output up to 100W LED
- Works at installation heights 1.8-2.5m
- Adjustable detection range 2-8m
- Adjustable time delay 10s to 7min
- Adjustable lux mode 10-2000lx
- Easy installation without wiring
- Can be installed at any time

### ORDERING INFORMATION

<b>Order code</b>	12308
<b>Description</b>	PIR Sensor to suit AT9819/TRI Series 30W and 50W Floods
<b>Item Code</b>	AT9819/TRI/SENS

### SENSOR (S SUFFIX)

<b>Adjustable Detection Area / Sensitivity</b>	Yes
<b>Adjustable Hold Time</b>	Yes
<b>Adjustable Standby Level</b>	No
<b>Corridor Function</b>	No
<b>Detection Range</b>	8 m
<b>Dusk Mode</b>	Yes
<b>Lux Adjustment</b>	Yes
<b>Lux Range</b>	10-2000lx lx
<b>Manual Override</b>	No
<b>Sensor Type</b>	PIR
<b>Switched Output</b>	No
<b>Time Delay</b>	10s - 7min

### WARRANTY

<b>Commercial Use Warranty</b>	2 RTB (Total 2 Years)
<b>Domestic Use Warranty</b>	2 (Yr) RTB



### DIMENSIONS

<b>Product Height</b>	70 mm
<b>Product Length</b>	44 mm
<b>Product Width</b>	44 mm

### LINE DRAWINGS

#### AT9819/TRI/SENS

