



Xiaomi RA75 WiFi Range Extender AC1200 User Guide

January 22, 2022 January 24, 2022

[Home](#) » [Xiaomi](#) » [Xiaomi RA75 WiFi Range Extender AC1200 User Guide](#) 



xiaomi

All images are for illustration purposes only and may differ from the actual product by model and region.

Contents [[hide](#)]

[1 About this product](#)

[2 Installation](#)

[3 FAQs \(frequently asked questions\)](#)


[4 Specifications:](#)

[5 Documents / Resources](#)

[5.1 Related Manuals / Resources](#)

About this product

The Mi WiFi Range Extender AC1200 is designed to extend the range of your home WiFi network.



1. Signal Indicator

Solid blue: The range extender is connected to your existing network and receives a strong signal.

Solid orange: The range extender is receiving a weak signal. Relocating the extender closer to the router is recommended.

Solid red: The range extender is disconnected from the network. Trying to relocate it within the range of your router.

Flashing red: The range extender is ready for initialization. **Off:** The range extender is unready for connection.

2. System Indicator

Solid blue: The system runs normally.

Flashing blue: WPS is processing.
Solid orange: The system is booting.
Flashing orange: The system is upgrading.
Off: No power.

- 3. WPS Button**
Press to launch the WPS Wizard.
- 4. Reset Button**
Press and hold for at least 5 seconds to restore factory settings.

Installation

- 1. Step1: Power On**
Plug the range extender into a power outlet close to your router. Wait until the 'Signal' indicator turns flashing red.
- 2. Step2: Set Up**
Method 1: APP Setup (Recommended)
Download the Mi Home APP/Xiaomi Home App and follow the in-app instructions to complete the setup.



Method 2: WPS Button Setup

- ① Press the WPS button on your router if it has one.
- ② Within 2 minutes press the WPS button on the range extender. The 'Signal' indicator should turn solid blue once the connection is successful.

Default Extended WiFi Name and Password after setup

- ① 2.4G WiFi: Router's WiFi name with '_Plus' at the end
 - ② 5G WiFi: Router's WiFi name with '_Plus_5G' at the end
 - ③ Password: Same as the router
- 3. Step3: Reposition your range extender**
Plug your range extender in a place between your router and the WiFi dead zone. To achieve better signal quality, try to find a location where the 'Signal' indicator is solid blue. If it doesn't, relocate the range extender closer to the router.



FAQs (frequently asked questions)

- Q1. What should I do if the Mi Home APP/Xiaomi Home App doesn't find my device during setup?
You can manually find Mi WiFi Range Extender AC1200 in the in-app device list and add it following the instructions.
- Q2. What should I do if the Mi WiFi Range Extender AC1200 stops working?

1. If the signal is poor, move the range extender to another location where there are no large obstacles between the range extender and the router.
2. If the range extender is offline, check that the router is emitting a WiFi signal. If the router is working normally, restart the range extender and try again.
3. Check whether the range extender was blacklisted by your router.
4. If the issue persists, hold down the reset button for at least 4 5 seconds until the indicator is constant orange. Reconfigure the settings and try again.

Q3.How do I configure the settings if I want to connect the range extender to a new Wi-Fi network?
Reset the range extender to factory settings and reconfigure the settings.

Specifications:

Name: Mi WiFi Range Extender AC1200

Model: RA75

Operating Temperature: 0-40°C

Input: 100~240VAC, 50/60Hz, 0.3A

Operating Frequency: 2400MHz~2483.5MHz 5150MHz~5350MHz, 5470MHz~5725MHz, 5725MHz~5850MHz



Certifications:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution:

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20 cm between the radiator and your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Manufactured by: Xiaomi Communications Co., Ltd
#019, Floor 9, Building 6, Yard 33, Middle Xi'erqi Road, Haidian
District, Beijing, China

Documents / Resources



[Xiaomi RA75 WiFi Range Extender AC1200](#) [pdf] User Guide RA75, 2AFZZRA75, RA75 WiFi Range Extender AC1200, WiFi Range Extender AC1200

All rights reserved for this or other trademarks and services.
All other trademarks are the property of their respective owners.

Related Manuals / Resources



[ICODE WiFi Range Extender Instructions](#)

ICODE WiFi Range Extender Instructions Introduction Dear customer
Thank you for purchasing on ICODE EX 300 wifi extender...



[tp-link AC750 WiFi Range Extender User Guide](#)

tp-link AC750 WiFi Range Extender User Guide - Download [optimized] tp-link AC750 WiFi Range Extender User Guide -...



[NETGEAR EX5000 AC1200 WiFi Range Extender User Guide](#)

Quick Start AC1200 WiFi Range Extender Model EX5000 LED descriptions
LED Description Power • Blinking green. The extender...



[MERCUSYS MW300RE 300Mbps WiFi Range Extender Installation Guide](#)

Quick Installation Guide Range Extender For technical support, the user guide, and more information, please visit
<http://www.mercusys.com/en/support>. Power...

[Manuals+](#),

- [home](#)
- [privacy](#)