



## Appendix C

### RF Test Data for 2.4GWIFI (Conducted Measurement)

Product Name: POS Terminal

Test Model: P600

#### Environmental Conditions

Temperature:	23.8° C
Relative Humidity:	52.2%
ATM Pressure:	100.0 kPa
Test Engineer:	Ling Zhu
Supervised by:	Li huan





### C.1 -6dB Bandwidth

Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	b	2412	Ant1	6.818	$\geq 0.5$	Pass
NVNT	b	2437	Ant1	7.286	$\geq 0.5$	Pass
NVNT	b	2462	Ant1	7.651	$\geq 0.5$	Pass
NVNT	g	2412	Ant1	15.285	$\geq 0.5$	Pass
NVNT	g	2437	Ant1	16.338	$\geq 0.5$	Pass
NVNT	g	2462	Ant1	16.341	$\geq 0.5$	Pass
NVNT	n20	2412	Ant1	17.496	$\geq 0.5$	Pass
NVNT	n20	2437	Ant1	17.531	$\geq 0.5$	Pass
NVNT	n20	2462	Ant1	17.726	$\geq 0.5$	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.  
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China  
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com  
Scan code to check authenticity




Test Graphs

-6dB Bandwidth NVNT b 2412MHz Ant1




-6dB Bandwidth NVNT b 2437MHz Ant1






-6dB Bandwidth NVNT b 2462MHz Ant1




-6dB Bandwidth NVNT g 2412MHz Ant1






-6dB Bandwidth NVNT g 2437MHz Ant1




-6dB Bandwidth NVNT g 2462MHz Ant1







-6dB Bandwidth NVNT n20 2412MHz Ant1



-6dB Bandwidth NVNT n20 2437MHz Ant1







## C.2 Maximum Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	b	2412	Ant1	15.53	30	Pass
NVNT	b	2437	Ant1	15.2	30	Pass
NVNT	b	2462	Ant1	14.25	30	Pass
NVNT	g	2412	Ant1	15.22	30	Pass
NVNT	g	2437	Ant1	15.27	30	Pass
NVNT	g	2462	Ant1	14.12	30	Pass
NVNT	n20	2412	Ant1	14.42	30	Pass
NVNT	n20	2437	Ant1	14.39	30	Pass
NVNT	n20	2462	Ant1	14.01	30	Pass







### C.3 Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Antenna	Total PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	b	2412	Ant1	-7.25	8	Pass
NVNT	b	2437	Ant1	-8.73	8	Pass
NVNT	b	2462	Ant1	-8.07	8	Pass
NVNT	g	2412	Ant1	-13.21	8	Pass
NVNT	g	2437	Ant1	-13.33	8	Pass
NVNT	g	2462	Ant1	-14.44	8	Pass
NVNT	n20	2412	Ant1	-13.68	8	Pass
NVNT	n20	2437	Ant1	-13.76	8	Pass
NVNT	n20	2462	Ant1	-16.15	8	Pass








Test Graphs

PSD NVNT b 2412MHz Ant1




PSD NVNT b 2437MHz Ant1











PSD NVNT g 2437MHz Ant1



PSD NVNT g 2462MHz Ant1









### C.4 Band Edge

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	b	2412	Ant1	-47.46	-20	Pass
NVNT	b	2462	Ant1	-63.79	-20	Pass
NVNT	g	2412	Ant1	-34.2	-20	Pass
NVNT	g	2462	Ant1	-41.1	-20	Pass
NVNT	n20	2412	Ant1	-35.33	-20	Pass
NVNT	n20	2462	Ant1	-41.23	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.  
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China  
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com  
Scan code to check authenticity




Test Graphs

Band Edge NVNT b 2412MHz Ant1 Ref




Band Edge NVNT b 2412MHz Ant1 Emission








Band Edge NVNT b 2462MHz Ant1 Ref




Band Edge NVNT b 2462MHz Ant1 Emission






Band Edge NVNT g 2412MHz Ant1 Ref




Band Edge NVNT g 2412MHz Ant1 Emission










Band Edge NVNT g 2462MHz Ant1 Ref



Band Edge NVNT g 2462MHz Ant1 Emission









### C.5 Conducted RF Spurious Emission

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	b	2412	Ant1	-51.83	-20	Pass
NVNT	b	2437	Ant1	-51.94	-20	Pass
NVNT	b	2462	Ant1	-52.08	-20	Pass
NVNT	g	2412	Ant1	-47.8	-20	Pass
NVNT	g	2437	Ant1	-47.57	-20	Pass
NVNT	g	2462	Ant1	-49.32	-20	Pass
NVNT	n20	2412	Ant1	-44.36	-20	Pass
NVNT	n20	2437	Ant1	-47.23	-20	Pass
NVNT	n20	2462	Ant1	-48.9	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.  
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China  
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com  
Scan code to check authenticity




Test Graphs

Tx. Spurious NVNT b 2412MHz Ant1 Ref




Tx. Spurious NVNT b 2412MHz Ant1 Emission






Tx. Spurious NVNT b 2437MHz Ant1 Ref




Tx. Spurious NVNT b 2437MHz Ant1 Emission








Tx. Spurious NVNT b 2462MHz Ant1 Ref




Tx. Spurious NVNT b 2462MHz Ant1 Emission






Tx. Spurious NVNT g 2412MHz Ant1 Ref




Tx. Spurious NVNT g 2412MHz Ant1 Emission






Tx. Spurious NVNT g 2437MHz Ant1 Ref




Tx. Spurious NVNT g 2437MHz Ant1 Emission






Tx. Spurious NVNT g 2462MHz Ant1 Ref




Tx. Spurious NVNT g 2462MHz Ant1 Emission






Tx. Spurious NVNT n20 2412MHz Ant1 Ref




Tx. Spurious NVNT n20 2412MHz Ant1 Emission






Tx. Spurious NVNT n20 2437MHz Ant1 Ref




Tx. Spurious NVNT n20 2437MHz Ant1 Emission






Tx. Spurious NVNT n20 2462MHz Ant1 Ref



Tx. Spurious NVNT n20 2462MHz Ant1 Emission





### C.6 Duty Cycle

Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	b	2412	Ant1	97.66	0.1	0.12
NVNT	b	2437	Ant1	97.66	0.1	0.12
NVNT	b	2462	Ant1	97.66	0.1	0.12
NVNT	g	2412	Ant1	87.29	0.59	0.74
NVNT	g	2437	Ant1	87.29	0.59	0.74
NVNT	g	2462	Ant1	87.29	0.59	0.74
NVNT	n20	2412	Ant1	86.53	0.63	0.79
NVNT	n20	2437	Ant1	86.53	0.63	0.79
NVNT	n20	2462	Ant1	86.53	0.63	0.79




Shenzhen LCS Compliance Testing Laboratory Ltd.  
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China  
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com  
Scan code to check authenticity






Test Graphs

Duty Cycle NVNT b 2412MHz Ant1




Duty Cycle NVNT b 2437MHz Ant1






Duty Cycle NVNT b 2462MHz Ant1




Duty Cycle NVNT g 2412MHz Ant1






Duty Cycle NVNT g 2437MHz Ant1




Duty Cycle NVNT g 2462MHz Ant1







Duty Cycle NVNT n20 2412MHz Ant1



Duty Cycle NVNT n20 2437MHz Ant1







### C.7 Restrict Band

Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	b	2412	Ant1	2310	-50.33	2	46.93	Peak	74	Pass
NVNT	b	2412	Ant1	2310	-60.65	2	36.61	Average	54	Pass
NVNT	b	2412	Ant1	2340.654	-47.77	2	49.49	Peak	74	Pass
NVNT	b	2412	Ant1	2389.677	-60.04	2	37.22	Average	54	Pass
NVNT	b	2412	Ant1	2390	-51.07	2	46.19	Peak	74	Pass
NVNT	b	2412	Ant1	2390	-60.05	2	37.21	Average	54	Pass
NVNT	b	2462	Ant1	2483.5	-46.38	2	50.88	Peak	74	Pass
NVNT	b	2462	Ant1	2483.5	-56.43	2	40.83	Average	54	Pass
NVNT	b	2462	Ant1	2485.478	-45.49	2	51.77	Peak	74	Pass
NVNT	b	2462	Ant1	2486.485	-56.13	2	41.13	Average	54	Pass
NVNT	b	2462	Ant1	2500	-51.41	2	45.85	Peak	74	Pass
NVNT	b	2462	Ant1	2500	-59.86	2	37.4	Average	54	Pass
NVNT	g	2412	Ant1	2310	-49.88	2	47.38	Peak	74	Pass
NVNT	g	2412	Ant1	2310	-60.29	2	36.97	Average	54	Pass
NVNT	g	2412	Ant1	2389.56	-38.54	2	58.72	Peak	74	Pass
NVNT	g	2412	Ant1	2389.911	-54.56	2	42.7	Average	54	Pass
NVNT	g	2412	Ant1	2390	-42.18	2	55.08	Peak	74	Pass
NVNT	g	2412	Ant1	2390	-54.2	2	43.06	Average	54	Pass
NVNT	g	2462	Ant1	2483.5	-33.97	2	63.29	Peak	74	Pass
NVNT	g	2462	Ant1	2483.5	-48.38	2	48.88	Average	54	Pass
NVNT	g	2462	Ant1	2484.153	-31.41	2	65.85	Peak	74	Pass
NVNT	g	2462	Ant1	2483.517	-48.38	2	48.88	Average	54	Pass
NVNT	g	2462	Ant1	2500	-50.99	2	46.27	Peak	74	Pass
NVNT	g	2462	Ant1	2500	-59.41	2	37.85	Average	54	Pass
NVNT	n20	2412	Ant1	2310	-50.99	2	46.27	Peak	74	Pass
NVNT	n20	2412	Ant1	2310	-60.15	2	37.11	Average	54	Pass
NVNT	n20	2412	Ant1	2389.794	-38.66	2	58.6	Peak	74	Pass
NVNT	n20	2412	Ant1	2389.911	-54.17	2	43.09	Average	54	Pass
NVNT	n20	2412	Ant1	2390	-41.51	2	55.75	Peak	74	Pass
NVNT	n20	2412	Ant1	2390	-53.78	2	43.48	Average	54	Pass
NVNT	n20	2462	Ant1	2483.5	-32.37	2	64.89	Peak	74	Pass
NVNT	n20	2462	Ant1	2483.5	-45.87	2	51.39	Average	54	Pass
NVNT	n20	2462	Ant1	2484.153	-29.62	2	67.64	Peak	74	Pass
NVNT	n20	2462	Ant1	2483.517	-45.87	2	51.39	Average	54	Pass
NVNT	n20	2462	Ant1	2500	-50.65	2	46.61	Peak	74	Pass
NVNT	n20	2462	Ant1	2500	-59.6	2	37.66	Average	54	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.  
 Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China  
 Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com  
 Scan code to check authenticity




Test Graphs

Restrict Band NVNT b 2412MHz Ant1 Peak




Restrict Band NVNT b 2412MHz Ant1 Average






Restrict Band NVNT b 2462MHz Ant1 Peak




Restrict Band NVNT b 2462MHz Ant1 Average








Restrict Band NVNT g 2412MHz Ant1 Peak




Restrict Band NVNT g 2412MHz Ant1 Average






Restrict Band NVNT g 2462MHz Ant1 Peak




Restrict Band NVNT g 2462MHz Ant1 Average






Restrict Band NVNT n20 2412MHz Ant1 Peak




Restrict Band NVNT n20 2412MHz Ant1 Average





Restrict Band NVNT n20 2462MHz Ant1 Peak



Restrict Band NVNT n20 2462MHz Ant1 Average

