

NINA-B4 series certification

Stand-alone Bluetooth 5.1 low energy modules

Application note

Abstract

This application note describes the requirements for utilizing the existing regulatory certifications and declarations associated with NINA-B4 series modules.

Document information

Title	NINA-B4 series	
Subtitle	Stand-alone Bluetooth 5.1 low energy modules	
Document type	Application note	
Document number	UBX-20037320	
Revision and date	R01	19-Nov-2020
Disclosure restriction	C1-Public	

This document applies to the following products:

Product name
NINA-B400
NINA-B406
NINA-B410
NINA-B416

u-blox or third parties may hold intellectual property rights in the products, names, logos and designs included in this document. Copying, reproduction, modification or disclosure to third parties of this document or any part thereof is only permitted with the express written permission of u-blox.

The information contained herein is provided "as is" and u-blox assumes no liability for its use. No warranty, either express or implied, is given, including but not limited to, with respect to the accuracy, correctness, reliability and fitness for a particular purpose of the information. This document may be revised by u-blox at any time without notice. For the most recent documents, visit www.u-blox.com.

Copyright © u-blox AG.

Contents

Document information	2
Contents	3
1 Qualification status.....	4
2 Qualification and approvals by country.....	5
2.1 European Union regulatory compliance	5
2.1.1 Radio Equipment Directive (RED) 2014/53/EU	5
2.1.2 Compliance with the RoHS directive	5
2.2 United States (FCC)	6
2.2.1 FCC compliance	6
2.2.2 FCC statement.....	7
2.2.3 RF-exposure.....	8
2.2.4 End-product compliance	8
2.3 Canada (ISED).....	8
2.3.1 Labeling and user information requirements	9
2.4 Japan radio equipment compliance.....	9
2.4.1 Compliance statement.....	9
2.4.2 End product labelling requirement.....	9
2.4.3 End product user manual requirement.....	10
2.5 NCC Taiwan compliance.....	10
2.5.1 Taiwan NCC Warning Statement.....	10
2.5.2 Labeling requirements for end product	10
2.6 KCC South Korea compliance.....	10
2.7 Brazil compliance	11
2.8 Australia and New Zealand regulatory compliance	11
2.9 South Africa regulatory compliance	12
2.10 Bluetooth qualification.....	12
3 Pre-approved antennas list.....	13
3.1 Antenna accessories	13
3.2 Single band antennas	13
Appendix	16
A Glossary	16
Related documentation.....	17
Revision history	18
Contact.....	19

1 Qualification status

 Approvals are pending.

NINA-B4x0 and NINA-B4x6 modules are certified for use in the following countries/regions:

Country/region	NINA-B4x0	NINA-B4x6
Europe	Approved	Approved
USA	Pending	Pending
Canada	Pending	Pending
Japan	Pending	Pending
Taiwan	Pending	Pending
South Korea	Pending	Pending
Brazil	Pending	Pending
Australia	Pending	Pending
New Zealand	Pending	Pending
South Africa	Pending	Pending

Table 1: Country certification status for the NINA-B4 series modules

2 Qualification and approvals by country

2.1 European Union regulatory compliance

For information about the regulatory compliance of NINA-B4 series modules against requirements and provisions in the European Union, see NINA-B4 Declaration of Conformity [1].

2.1.1 Radio Equipment Directive (RED) 2014/53/EU


NINA-B4 series modules comply with the essential requirements and other relevant provisions of Radio Equipment Directive (RED) 2014/53/EU.


2.1.2 Output power limitation

The Radio Equipment Directive requires radio transmitters that have an Equivalent Isotropically Radiated Power (EIRP) of 10 dBm or more, to either implement an adaptivity feature or reduce its medium utilization.

The NINA-B4 series modules are based on the Nordic Semiconductor nRF52833 chip, which supports multiple radio protocols such as Bluetooth low energy, IEEE 802.15.4 with thread etc.

Since Bluetooth low energy does not support either adaptivity or reduced medium utilization, a NINA-B4 Bluetooth LE implementation on the European market must have an EIRP of less than 10 dBm.

 In the European market, it is the end product manufacturer that holds the responsibility that these limitations are followed. If the u-blox module integrator is not the end product manufacturer, the module integrator should make sure that this information is shared with the end product manufacturer.

 Radio protocols based on 802.15.4, which supports adaptivity is allowed an EIRP of 10 dBm or higher.

EIRP is calculated as:

$$\text{EIRP(dBm)} = P_{\text{TX}}(\text{dBm}) - L(\text{dB}) + G_{\text{TX}}(\text{dBi})$$

where P_{TX} is the output power of the transmitter, L is the path loss of the transmission line between the transmitter and antenna, and G_{TX} is the maximum gain of the transmit antenna. Consider the following for each of these components:

- Output power:
 - The output power setting of the NINA-B4 module. An end product user must not be able to increase the setting above the 10 dBm EIRP limit, by sending configuration commands etc.
 - The operating temperature of the end product. The output power of a transmitter is typically increased as the ambient temperature is lowered. The operating temperature range of NINA-B4 is -40 to +105 °C, and across this range the output power can typically vary by 1 dB. The output power at the lowest operating temperature (yielding the highest output power) must be considered for the EIRP calculation.
- Path loss – Long antenna cables or PCB traces, RF switches, etc. will attenuate the power reaching the antenna. This path loss should be measured and taken into consideration for the EIRP calculation.
- Antenna gain - The maximum gain of the transmit antenna must be considered for the EIRP calculation.

2.1.3 Compliance with the RoHS directive

NINA-B4 series modules comply with the Directive 2011/65/EU (EU RoHS 2) and its amendment Directive (EU) 2015/863 (EU RoHS 3).

2.2 United States (FCC)

Approvals are pending.

Any changes or modifications NOT explicitly APPROVED by u-blox AG may make the module non-compliant with FCC rules part 15 and subsequently void the user's authority to operate the equipment.

2.2.1 FCC compliance

NINA-B4 series modules are intended for OEM integrators only. The end product must be professionally installed in way that only authorized antennas can be used. The (OEM) Integrator must assure compliance of the entire end product that includes the integrated NINA-B4 module.

For compliance with FCC Part 15B (§15.107, and if applicable §15.109 regulations, the host manufacturer is required to show conformant operation of the installed product. The product evaluation should also confirm that the intentional emissions (15C) from the module are compliant during (fundamental/out-of-band) transmission. Additionally, the integrator must apply the appropriate equipment authorization (verification) for the new host device as defined in §15.101.

The details of the module implementation in host device is confidential. Integrators are reminded not to share the installation instructions of the module to the end-user of the final host device.

The final host device, into which this RF Module is integrated must be labeled with an auxiliary label stating the FCC ID of the RF Module, such as:


“Contains FCC ID: **TBD**”

"This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that might cause undesired operation.”

"Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment."

The Integrator is responsible for satisfying SAR/ RF exposure requirements once the module has been integrated into the host device.

 NINA-B4 series modules are intended for OEM integrators only. End products that include u-blox modules must be professionally installed in way that only authorized antennas can be used. See section 2.1 for more information.

Model	FCC ID
NINA-B400	TBD
NINA-B406	TBD
NINA-B410	TBD
NINA-B416	TBD


Table 02: FCC ID for the NINA-B4 series modules

2.2.2 FCC statement

The single-modular transmitter supported in NINA-B4 modules is a self-contained, physically delineated, component for which compliance can be demonstrated independent of the host operating conditions.

The transmitter complies with all eight requirements of § 15.212(a)(1), as summarized below:

1. The radio elements have the radio frequency circuitry shielded.
2. The module has buffered modulation/data inputs to ensure that the device will comply with Part 15 requirements with any type of input signal.
3. The module contains power supply regulation on the module.
4. The module contains a permanently attached antenna.
5. The module demonstrates compliance in a stand-alone configuration.
6. The module is labeled with its permanently affixed FCC ID label.
7. The module complies with all specific rules applicable to the transmitter, including all the conditions provided in the integration instructions by the grantee.
8. The module complies with RF exposure requirements.

 This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

2.2.3 RF-exposure

All transmitters regulated by FCC must comply with RF exposure requirements. [KDB 447498 General RF Exposure Guidance](#) provides guidance in determining whether proposed or existing transmitting facilities, operations or devices comply with limits for human exposure to Radio Frequency (RF) fields adopted by the Federal Communications Commission (FCC).

NINA-B4 modules are approved for installation into mobile and/or portable host platforms and must not be co-located or operating in conjunction with any other antenna or transmitter – except in accordance with FCC multi-transmitter guidelines. End users must be provided with transmitter operating conditions for satisfying RF Exposure compliance.

2.2.4 IEEE 802.15.4 channel map limitation

The 2.4 GHz band used by 802.15.4 communications is segmented into 16 channels, ranging from channel 11 at 2405 MHz to channel 26 at 2480 MHz, with 5 MHz channel spacing. Due to the wide spectral properties of the 802.15.4 signal, the use of channel 26 results in too much power being transmitted in the FCC restricted band starting at 2483.5 MHz. As a result, channel 26 must not be used on the US/Canadian market.

2.2.5 End-product compliance

Application designs must conform to the following requirements:

- Any changes to hardware, hosts or co-location configuration may require new radiated emission and SAR evaluation and/or testing.
- Only authorized antenna(s) may be used.
- Any notification to the end user about how to install or remove the integrated radio module is NOT allowed.
- The approval of the modular transmitter in NINA-B4 series modules does not exempt the end product from being evaluated against any applicable regulatory demands. The evaluation of the end product shall be performed with the NINA-B4 module installed and operating in a way that reflects the intended use case of the end product. The upper frequency measurement range for the end product evaluation is the 5th harmonic of 2.4 GHz as declared in 47 CFR Part 15.33 (b)(1).
- The following requirements apply to all products that integrate a radio module:
 - Subpart B - UNINTENTIONAL RADIATORS
To verify that the composite device of host and module complies with the requirements of FCC part 15B the integrator shall perform sufficient measurements using equipment compliant with ANSI 63.4-2014.
 - Subpart C - INTENTIONAL RADIATORS
The integrator must carry out sufficient verification measurements, using compliant ANSI 63.10-2013 equipment, to validate that the fundamental and out-of-band emissions of the transmitter part of the composite device comply with the requirements of FCC part 15C.
- When the items listed above are fulfilled the host manufacturer can use the authorization procedures presented in Table 1 of 47 CFR Part 15.101.

2.3 Canada (ISED)

Approvals are pending.

NINA-B4 series module are certified for use in accordance with the Canada under Innovation, Science and Economic Development Canada (ISED) Radio Standards Specification (RSS) RSS-247 Issue 2 and RSSGen.

2.3.1 Labeling and user information requirements

The final host device, into which this RF Module is integrated, must be labeled with an auxiliary label stating the IC of the RF Module, such as:

“Contains transmitter module IC: TBD”

Le périphérique hôte final, dans lequel ce module RF est intégré "doit être étiqueté avec une étiquette auxiliaire indiquant le CI du module RF, tel que" Contient le module émetteur IC: TBD

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions:

1. This device may not cause interference, and
2. This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

1. L'appareil ne doit pas produire de brouillage, et

L'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Model	IC number
NINA-B400	TBD
NINA-B406	TBD
NINA-B410	TBD
NINA-B416	TBD

Table 03: IC for the NINA-B4 series modules

2.4 Japan radio equipment compliance

 Approvals are pending.

2.4.1 Compliance statement

NINA-B4 series modules comply with the Japanese Technical Regulation Conformity Certification of Specified Radio Equipment (ordinance of MPT N°. 37, 1981), Article 2, Paragraph 1:

- Item 19 "2.4 GHz band wide band low power data communication system".

2.4.2 End product labelling requirement

End products based on NINA-B4 series modules and targeted for distribution in Japan must be affixed with a label with the “Giteki” marking, as shown in Figure 1. The marking must be visible for inspection.



Figure 1: Giteki mark  and NINA-B4 MIC certification number

2.4.3 End product user manual requirement

As the MIC ID (represented as xxx-yyy in Figure 1) is not included on the NINA-B4 marking, the end product manufacturer must include a copy of the NINA-B4 Japan Radio Certificate in the end product technical documentation.

2.5 NCC Taiwan compliance

 Approvals are pending.

2.5.1 Taiwan NCC Warning Statement

- 經型式認證合格之低功率射頻電機，非經許可，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。
- 低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前項合法通信，指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

Statement translation:

- Without permission granted by the NCC, any company, enterprise, or user is not allowed to change frequency, enhance transmitting power, or alter original characteristic as well as performance to an approved low power radio-frequency device.
- The low power radio-frequency devices shall not influence aircraft security and interfere legal communications; If any interference is found or suspected, the user shall immediately cease operating the equipment until the interference has been prevented. The said legal communications means radio communications is operated in compliance with the Telecommunications Act. The low power radio-frequency devices must be susceptible with the interference from legal communications or ISM radio wave radiated devices.

2.5.2 Labeling requirements for end product

End products based on NINA-B4 series modules and targeted for distribution in Taiwan must carry labels with the textual and graphical elements shown below.

Contains Transmitter Module

內含發射器模組:  xxxxxxxxyyyyyyy


Other wording can be used, but only if the meaning of original messaging remains unchanged. The label must be physically attached to the product and made clearly visible for inspection.

2.6 KCC South Korea compliance

 Approvals are pending.

NINA-B4 series modules are certified by the Korea Communications Commission (KCC).

End products based on NINA-B4 series modules and targeted for distribution in South Korea must carry labels containing the KCC logo and certification number, as shown below. This information must also be included in the product user manuals.

 x-x-xx-yyyy-yyyy

 The height of the KCC logo must be at least 5 mm.

2.7 Brazil compliance

Approvals are pending.

End products based on NINA-B4 series modules and targeted for distribution in Brazil must carry labels that include the Anatel logo, NINA-B4 Homologation number: xxxxx-xx-yyyyy and a statement claiming that the device may not cause harmful interference but must accept it (Resolution No 506).



“Este equipamento opera em caráter secundário, isto é, não tem direito a proteção contra interferência prejudicial, mesmo de estações do mesmo tipo, e não pode causar interferência a sistemas operando em caráter primário.”

Statement translation:

“This equipment operates on a secondary basis and, consequently, must accept harmful interference, including from stations of the same kind, and may not cause harmful interference to systems operating on a primary basis.”

When the device is so small or for such use that it is not practicable to place the statement above on the label, the information shall be placed in a prominent location in the instruction manual or pamphlet supplied to the user or, alternatively, shall be placed on the container in which the device is marketed.

In cases where the final product is to be installed in locations where the end user is unable to see the Anatel logo, NINA-B4 Homologation number and/or statement, these graphical and textual elements must be included in the end product manual.

2.8 Australia and New Zealand regulatory compliance

Approvals are pending.



The NINA-B4 module is compliant with the standards made by the Australian Communications and Media Authority (ACMA).

The modules are compliant with AS/NZS 4268:2012 standard – Radio equipment and systems – Short range devices – Limits and methods of standard measurement. The test reports for NINA-B4 modules can be used as part of the product certification and compliance folder. For more information on the test reports, email the respective support team at the local mail address in your region. See Contact .

To meet the overall Australian and/or New Zealand end product compliance standards, the integrator must create a compliance folder containing all the relevant compliance test reports such as RF, EMC, electrical safety and DoC (Declaration of Conformity). It is the responsibility of the integrator to know what is required in the compliance folder for ACMA compliance.

For more information on Australia compliance, refer to the Australian Communications and Media Authority web site <http://www.acma.gov.au/>.

For more information on New Zealand compliance, refer to the New Zealand Radio Spectrum Management Group web site www.rsm.govt.nz.

2.9 South Africa regulatory compliance

Approvals are pending.

NINA-B4 series modules are compliant and certified by the Independent Communications Authority of South Africa (ICASA). End products that are made available for sale or lease or supplied in any other manner in South Africa shall have a legible label permanently affixed to its exterior surface. The label shall include the ICASA logo and the ICASA issued license number, as shown in the figure below. The minimum width and height of the ICASA logo shall be 3 mm. The approval labels must be purchased by the customer's local representative directly from the approval authority ICASA. A sample of a NINA-B4 ICASA label is shown below:



More information on registration as a Responsible Integrator and labeling requirements can be found at the following website:

Independent Communications Authority of South Africa (ICASA) web site - <https://www.icasa.org.za>

2.10 Bluetooth qualification



NINA-B4 module series modules have been qualified as an end product in accordance with the Bluetooth 5.1 specification.

Product type	QD ID	Listing Date
End product	157158	2020-10-13

Table 1: NINA-B4 series Bluetooth qualified design ID

3 Pre-approved antennas list

This section lists the different external antennas that are pre-approved for use together with the NINA-B4 series modules.

Note that not all antennas are approved for use in all markets/regions.

3.1 Antenna accessories

Name	U.FL to SMA adapter cable
Connector	U.FL and SMA jack (outer thread and pin receptacle)
Impedance	50 Ω
Minimum cable loss	0.5 dB, The cable loss must be above the minimum cable loss to meet the regulatory requirements. Minimum cable length 100 mm.
Comment	The SMA connector can be mounted in a panel. See NINA-B4 Series system integration manual [2] for information how to integrate the U.FL connector.
Approval	RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



Name	U.FL to Reverse Polarity SMA adapter cable
Connector	U.FL and Reverse Polarity SMA jack (outer thread and pin)
Impedance	50 Ω
Minimum cable loss	0.5 dB, The cable loss must be above the minimum cable loss to meet the regulatory requirements. Minimum cable length 100 mm.
Comment	The Reverse Polarity SMA connector can be mounted in a panel. See NINA-B4 Series system integration manual [2] for information how to integrate the U.FL connector. It is required to followed this reference design to comply with the NINA-B4 FCC/IC modular approvals.
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



3.2 Single band antennas

NINA-B406 and NINA-B416	
Manufacturer	ProAnt
Gain	+3 dBi
Impedance	N/A
Size (HxWxL)	1.1 x 3.4 x 10 mm
Type	PCB trace
Comment	PCB antenna on NINA-B406 and NINA-B416. Should not be mounted inside a metal enclosure.
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



GW.26.0111	
Manufacturer	Taoglas
Polarization	Vertical
Gain	+2.0 dBi
Impedance	50 Ω
Size	Ø 7.9 x 30.0 mm
Type	Monopole



Connector	SMA (M) .
Comment	To be mounted on the U.FL to SMA adapter cable.
Approval	RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA

Ex-IT 2400 RP-SMA 28-001

Manufacturer	ProAnt
Polarization	Vertical
Gain	+3.0 dBi
Impedance	50 Ω
Size	Ø 12.0 x 28.0 mm
Type	Monopole
Connector	Reverse Polarity SMA plug (inner thread and pin receptacle).
Comment	This antenna requires to be mounted on a metal ground plane for best performance. To be mounted on the U.FL to Reverse Polarity SMA adapter cable. An SMA version antenna is also available but not recommended for use (Ex-IT 2400 SMA 28-001).
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



Ex-IT 2400 MHF 28-001

Manufacturer	ProAnt
Polarization	Vertical
Gain	+2.0 dBi
Impedance	50 Ω
Size	Ø 12.0 x 28.0 mm
Type	Monopole
Cable length	100 mm
Connector	U.FL. connector
Comment	This antenna requires to be mounted on a metal ground plane for best performance. To be mounted on a U.FL connector. See See NINA-B4 Series system integration manual [2] for information how to integrate the U.FL connector. It is required to followed this reference design to comply with the NINA-B4 FCC/IC modular approvals.
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



Ex-IT 2400 RP-SMA 70-002

Manufacturer	ProAnt
Polarization	Vertical
Gain	+3.0 dBi
Impedance	50 Ω
Size	Ø 10 x 83 mm
Type	Monopole
Connector	Reverse Polarity SMA plug (inner thread and pin receptacle)
Comment	To be mounted on the U.FL to Reverse Polarity SMA adapter cable. An SMA version antenna is also available but not recommended for use (Ex-IT 2400 SMA 70-002).
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



InSide-2400

Manufacturer	ProAnt
Gain	+3.0 dBi
Impedance	50 Ω
Size	27 x 12 mm (triangular)
Type	Patch
Cable length	100 mm
Connector	U.FL. connector
Comment	Should be attached to a plastic enclosure or part for best performance. To be mounted on a U.FL connector. See NINA-B4 Series system integration manual [2] for information how to integrate the U.FL connector. It is required to followed this reference design to comply with the NINA-B4 FCC/IC modular approvals.
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



FlatWhip-2400 SMA

Manufacturer	ProAnt
Gain	+3.0 dBi
Impedance	50 Ω
Size	Ø 50.0 x 30.0 mm
Type	Monopole
Connector	SMA plug (inner thread and pin)
Comment	To be mounted on the U.FL to SMA adapter cable.
Approval	RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



FlatWhip-2400 RP-SMA

Manufacturer	ProAnt
Gain	+3.0 dBi
Impedance	50 Ω
Size	Ø 50.0 x 30.0 mm
Type	Monopole
Connector	Reverse Polarity SMA plug (inner thread and pin receptacle).
Comment	To be mounted on the U.FL to SMA adapter cable.
Approval	FCC, IC, RED, MIC, NCC, KCC, ANATEL, ACMA and ICASA



Appendix


A Glossary

Abbreviation	Definition
FCC	Federal Communications Commission
ISED	Innovation, Science and Economic Development Canada
RED	Radio Equipment Directive
MIC	Ministry of Internal Affairs and Communications
NCC	National Communications Commission
KCC	Korea Communications Commission
ANATEL	Coordinated Universal Time
ACMA	Data Circuit-terminating Equipment* / Data Communication Equipment*
ICASA	Data Terminal Equipment

Table 2: Explanation of the abbreviations and terms used

Related documentation

- [1] NINA-B4 Declaration of Conformity, UBX-20043953
- [2] NINA-B4 Series system integration manual, UBX-19052230

 For product change notifications and regular updates of u-blox documentation, register on our website, www.u-blox.com.

Revision history

Revision	Date	Name	Comments
R01	19-Nov-2020	fkru	Initial release

Contact

For complete contact information, visit us at www.u-blox.com.

u-blox Offices

North, Central and South America

u-blox America, Inc.

Phone: +1 703 483 3180

E-mail: info_us@u-blox.com

Regional Office West Coast:

Phone: +1 408 573 3640

E-mail: info_us@u-blox.com

Technical Support:

Phone: +1 703 483 3185

E-mail: support@u-blox.com

Headquarters

Europe, Middle East, Africa

u-blox AG

Phone: +41 44 722 74 44

E-mail: info@u-blox.com

Support: support@u-blox.com

Asia, Australia, Pacific

u-blox Singapore Pte. Ltd.

Phone: +65 6734 3811

E-mail: info_ap@u-blox.com

Support: support_ap@u-blox.com

Regional Office Australia:

Phone: +61 2 8448 2016

E-mail: info_au@u-blox.com

Support: support_ap@u-blox.com

Regional Office China (Beijing):

Phone: +86 10 68 133 545

E-mail: info_cn@u-blox.com

Support: support_cn@u-blox.com

Regional Office China (Chongqing):

Phone: +86 23 6815 1588

E-mail: info_cn@u-blox.com

Support: support_cn@u-blox.com

Regional Office China (Shanghai):

Phone: +86 21 6090 4832

E-mail: info_cn@u-blox.com

Support: support_cn@u-blox.com

Regional Office China (Shenzhen):

Phone: +86 755 8627 1083

E-mail: info_cn@u-blox.com

Support: support_cn@u-blox.com

Regional Office India:

Phone: +91 80 405 092 00

E-mail: info_in@u-blox.com

Support: support_in@u-blox.com

Regional Office Japan (Osaka):

Phone: +81 6 6941 3660

E-mail: info_jp@u-blox.com

Support: support_jp@u-blox.com

Regional Office Japan (Tokyo):

Phone: +81 3 5775 3850

E-mail: info_jp@u-blox.com

Support: support_jp@u-blox.com

Regional Office Korea:

Phone: +82 2 542 0861

E-mail: info_kr@u-blox.com

Support: support_kr@u-blox.com

Regional Office Taiwan:

Phone: +886 2 2657 1090

E-mail: info_tw@u-blox.com

Support: support_tw@u-blox.com