

TEST REPORT

No.115N01121-EMC

for

TCL Communication Ltd

GSM Quad band &UMTS Dual band mobile phone

Model Name:2045X

FCC ID: 2ACCJB038

with

Hardware Version: PIO

Software Version: V1.0

Issued Date: 2015-10-20

Test Laboratory:

FCC 2.948 Listed: No.342690

Note:

The test results in this test report relate only to the devices specified in this report. This report shall not be reproduced except in full without the written approval of CTTL.

Test Laboratory:

CTTL, Telecommunication Technology Labs, Academy of Telecommunication Research, MIIT No.52, HuayuanNorth Road, Haidian District, Beijing, P. R. China 100191.

Tel:+86(0)10-62304633, Fax:+86(0)10-62304633Email:cttl@chinattl.com, website:www.chinattl.com



REPORT HISTORY

| Report Number | Revision | Description | Issue Date |
|---------------|----------|-------------|------------|
| I15N01121-EMC | Rev.0 | 1st edition | 2015-10-20 |



CONTENTS

| 1. | TEST LABORATORY | . 4 |
|------|--|-----|
| 1.1. | TESTINGLOCATION | . 4 |
| 1.2. | TESTINGENVIRONMENT | . 4 |
| 1.3. | PROJECT DATA | . 4 |
| 1.4. | SIGNATURE | . 4 |
| 2. | CLIENTINFORMATION | . 5 |
| 2.1. | APPLICANT INFORMATION | . 5 |
| 2.2. | MANUFACTURER INFORMATION | . 5 |
| 3. | EQUIPMENT UNDERTEST (EUT) AND ANCILLARY EQUIPMENT (AE) | . 6 |
| 3.1. | ABOUT EUT | . 6 |
| 3.2. | INTERNAL IDENTIFICATION OF EUT | . 6 |
| 3.3. | INTERNAL IDENTIFICATION OF AE | . 6 |
| 3.4. | EUT SET-UPS | . 7 |
| 4. | REFERENCE DOCUMENTS | . 8 |
| 4.1. | REFERENCE DOCUMENTS FOR TESTING | . 8 |
| 5. | LABORATORY ENVIRONMENT | . 9 |
| 6. | SUMMARY OF TEST RESULTS | 10 |
| 7. | TEST FACILITIES UTILIZED | .11 |
| A NI | NEV A. MEACHDEMENT DECHITC | 12 |



1. Test Laboratory

1.1. TestingLocation

Address:

TCL International E city No. 1001 Zhongshanyuan Road, Nanshan

District, Shenzhen, Guangdong, China

Postal Code:

518048

Telephone:

+86(755)33322000

Fax:

+86(755)33322000

1.2. TestingEnvironment

Normal Temperature:

15-35℃

Relative Humidity:

20-75%

1.3. Project data

Testing Start Date:

2014-11-24

Testing End Date:

2014-12-04

1.4. Signature

Liang Yong

(Prepared this test report)

Du Zhaoxuan

(Reviewed this test report)

Cao Junfei

Director of the laboratory

(Approved this test report)



2. ClientInformation

2.1. Applicant Information

Company Name: TCL Communication Ltd.

Address /Post: 5F, E building, No. 232, Liang Jing Road, ZhangJiang High-Tech

Park, Pudong Area, Shanghai, 201203, P.R. China

City: ShenZhen Postal Code: 518057

2.2. Manufacturer Information

Company Name: TCL Communication Ltd.

Address /Post: 5F, E building, No. 232, Liang Jing Road, ZhangJiang High-Tech

Park, Pudong Area, Shanghai, 201203, P.R. China

City: ShenZhen Postal Code: 518057



3. Equipment UnderTest (EUT) and Ancillary Equipment (AE)

3.1. About EUT

Description GSM Quad band &UMTS Dual band mobile phone

Model Name 2045X

FCC ID 2ACCJB038

Remark: The above EUT's information is declared by manufacturer. Please refer to the specifications or user's manual for more detailed information.

Note: The mobile phone 2045X manufactured by TCL Communication Ltd is a variant model based on 2045M for conformance test. According to the declaration of changes, no test needs to been performed. all results are cited from the initial model. The report number for initial model is I14N01400.

3.2. Internal Identification of EUT

EUT ID* SN or IMEI
N0.1 /

3.3. Internal Identification of AE

| AE ID* | Description | SN |
|--------|----------------|----|
| AE1 | Battery | / |
| AE2 | Travel charger | / |
| AE3 | USB cable | / |

AE1

Model CAB3120000C1

Manufacturer BYD
Capacitance 850mAh
Nominal voltage 3.8V

AE2

Model CBA3007AG0C1

Manufacturer BYD Length of cable 95cm

AE3

Model CDA0000029C3
Manufacturer JiaYiKang

Length of cable 95cm

^{*}EUT ID: is used to identify the test sample in the lab internally.

^{*}AE ID: is used to identify the test sample in the lab internally.



3.4. EUT set-ups

EUT set-up No. Combination of EUT and AE Remarks

Set.1 EUT1+ AE1 + AE2 Charging mode
Set.2 EUT1+ AE1 + AE3 USB mode



4. Reference Documents

4.1. Reference Documents for testing

The following documents listed in this section are referred for testing.

| Reference | Title | Version |
|--------------|--|-----------|
| FCC Part 15, | Padio fraguency devices | 10-1-2014 |
| Subpart B | Radio frequency devices | |
| | Methods of Measurement of Radio-Noise Emissions from | |
| ANSI C63.4 | Low-Voltage Electrical and Electronic Equipment in the | 2003 |
| | Range of 9 kHz to 40 GHz | |



5. LABORATORY ENVIRONMENT

Semi-anechoic chamber did not exceed following limits along the EMC testing:

| Min. = 15 °C, Max. = 30 °C |
|--|
| Min. = 35 %, Max. = 60 % |
| 0.014MHz-1MHz,>60dB; |
| 1MHz-1000MHz,>90dB |
| > 2MΩ |
| < 4 Ω |
| < ±4 dB, 3 m distance, from 30 to 1000 MHz |
| Between 0 and 6 dB, from 80 to 3000 MHz |
| |

Shidlded room did not exceed following limits along the EMC testing:

| Temperature | Min. = 15 °C, Max. = 30 °C |
|--------------------------|----------------------------|
| Relative humidity | Min. =35 %, Max. = 60 % |
| Shielding effectiveness | 0.014MHz-1MHz,>60dB; |
| | 1MHz-1000MHz,>90dB |
| Electrical insulation | > 2MΩ |
| Ground system resistance | <4 Ω |

Fully-anechoic chamber did not exceed following limits along the EMC testing:

| Temperature | Min. = 15 $^{\circ}$ C, Max. = 30 $^{\circ}$ C | |
|------------------------------------|--|--|
| Relative humidity | Min. = 35 %, Max. = 60 % | |
| Shielding effectiveness | 0.014MHz-1MHz,>60dB; | |
| | 1MHz-1000MHz,>90dB | |
| Electrical insulation | > 2MΩ | |
| Ground system resistance | < 4 Ω | |
| Voltage Standing Wave Ratio (VSWR) | ≤ 6 dB, from 1 to 6 GHz, 3 m distance | |



6. SUMMARY OF TEST RESULTS

| Abbreviations used in this clause: | |
|------------------------------------|----------------|
| Р | Pass |
| NA | Not applicable |
| F | Fail |

| Items | Test Name | Clause in FCC rules | Section in this report | Verdict |
|-------|--------------------|---------------------|------------------------|---------|
| 1 | Radiated Emission | 15.109(a) | A.1 | Р |
| 2 | Conducted Emission | 15.107(a) | A.2 | Р |



7. Test Facilities Utilized

| NO. | NAME | TYPE | SERIES | PRODUCER | CALDUE | CAL |
|-----|----------------------|----------|---------------------|--------------|------------|---|
| | | | NUMBER | | DATE | PERIOD |
| 1. | Test Receiver | ESCI | 100701 | R&S | 2016.08.10 | 1 year |
| 2. | Test Receiver | ESCI | 100702 | R&S | 2016.05.30 | 1 year |
| 3. | Spectrum Analyzer | FSP 40 | 100378 | R&S | 2015.12.19 | 1 year |
| 4. | BiLog Antenna | VULB9163 | 9163 329 | Schwarzbeck | 2017.01.20 | 3 years |
| 5. | LISN | ESH2-Z5 | 100196 | R&S | 2016.01.13 | 1 year |
| 6. | Horn Antenna | 3117 | 00066577 | ETS-Lindgren | 2016.04.01 | 3 years |
| 7. | Universal Radio | E5515C | CD44054334 | Agilont | 2016 05 10 | 1 ,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,, |
| | Communication Tester | ESSISC | GB44051324 | Agilent | 2016.05.19 | 1 year |
| 8. | PC | M4099t | SA08850737 | Lenovo | / | / |
| 9. | Monitor | L1710d | 0M04340B10 01010 | Lenovo | / | / |
| 10. | Printer | P1008 | VNF6C12491 | HP | / | / |
| 11. | Keyboard | KB-0225 | 0723779 | Lenovo | / | / |
| 12. | Mouse | MO28UOL | 44B39412 | Lenovo | / | / |



ANNEX A: MEASUREMENT RESULTS

A.1 Radiated Emission (§15.109(a))

Reference

FCC: CFR Part 15.109(a)

A.1.1 Method of measurement

The field strength of radiated emissions from the unintentional radiator (USB mode of MS and charging mode of MS) at a distance of 3 meters is tested. Tested in accordance with the procedures of ANSI C63.4 - 2003, section 8.3.

The EUT was placed on a non-conductive table. The measurement antenna was placed at a distance of 3 meters from the EUT. During the tests, the antenna height and the EUT azimuth were varied in order to identify the maximum level of emissions from the EUT. This maximization process was repeated with the EUT positioned in each of its three orthogonal orientations.

A.1.2 EUT Operating Mode:

The MS is operating in the USB mode and charging mode. During the test MS is connected to a PC via a USB cable in the case of USB mode and is connected to a charger in the case of charging mode. The model of the PC is Lenovo Thinkcentre M4099t, and the serial number of the PC is SA08850737. The software is used to let the PC keep on copying data to MS, reading and erasing the data after copy action was finished.

A.1.3 Measurement Limit

Limit from CFR Part 15.109(a)

| Frequency range | Field strength limit (µV/m) | | |
|-----------------|-----------------------------|---------|------|
| (MHz) | Quasi-peak | Average | Peak |
| 30-88 | 100 | | |
| 88-216 | 150 | | |
| 216-960 | 200 | | |
| 960-1000 | 500 | | |
| >1000 | | 500 | 5000 |

^{*}Note: The original limit is defined at 10m test distance. This limit is calculated according to CISPR requirements.

A.1.4 Test Condition

| Frequency of emission (MHz) | RBW/VBW | Sweep Time(s) |
|-----------------------------|-----------------------|---------------|
| 30-1000 | 120kHz (IF bandwidth) | 5 |
| Above 1000 | 1MHz/3MHz | 15 |



A.1.5 Measurement Results

A "reference path loss" is established and the A_{Rpl} is the attenuation of "reference path loss". It includes the antenna factor of receive antenna and the path loss.

The measurement results are obtained as described below:

Result = $P_{Mea} + A_{Rpl} = P_{Mea} + G_A + G_{PL}$

Where

G_A: Antenna factor of receive antenna

G_{PL}: Path Loss

P_{Mea}: Measurement result on receiver.

Note: the result contains vertical part and Horizontal part

RE Measurement uncertainty: 30M-1GHz: 5.08dB (K=2);

1GHz-18GHz: 4.56 dB (K=2)

Set.1 Charging mode / Peak detector

| Frequency(MHz) | Result(dBuV/m) | Polarity | A _{Rpl} (dB) | Margin(dB) | Limit |
|----------------|----------------|----------|-----------------------|------------|----------|
| 1 3() | , | , | , | , , | (dBµV/m) |
| 14212.000000 | 56.3 | Н | 12.7 | 17.7 | 74.0 |
| 14879.000000 | 57.0 | V | 13.6 | 17.0 | 74.0 |
| 15670.000000 | 59.3 | V | 13.8 | 14.7 | 74.0 |
| 16295.000000 | 59.0 | V | 14.8 | 15.0 | 74.0 |
| 16814.000000 | 59.9 | V | 15.4 | 14.1 | 74.0 |
| 17445.000000 | 58.5 | V | 15.6 | 15.5 | 74.0 |

Set.1 Charging mode / Average detector

| Frequency(MHz) | Result(dBuV/m) | Polarity | A _{Rpl} (dB) | Margin(dB) | Limit |
|----------------|--------------------|-----------|-----------------------|------------|----------|
| | 1100011(012017111) | · Gianity | 7 (Kpi (G-2) | a.g(a.2) | (dBµV/m) |
| 14403.000000 | 44.7 | Н | 13.4 | 9.3 | 54.0 |
| 14973.000000 | 45.2 | Н | 13.8 | 8.8 | 54.0 |
| 15779.000000 | 46.8 | V | 14.2 | 7.2 | 54.0 |
| 16324.000000 | 46.8 | Н | 15.0 | 7.2 | 54.0 |
| 16844.000000 | 47.4 | V | 15.6 | 6.6 | 54.0 |
| 17414.000000 | 47.1 | V | 15.6 | 6.9 | 54.0 |



Set.2 USB mode / Peak detector

| Frequency(MHz) | Result(dBuV/m) | Polarity | A _{Rpl} (dB) | Margin(dB) | Limit |
|----------------|----------------|----------|-----------------------|------------|----------|
| | | | | | (dBµV/m) |
| 14446.000000 | 56.6 | Н | 13.1 | 17.4 | 74.0 |
| 15158.000000 | 57.0 | V | 13.0 | 17.0 | 74.0 |
| 15653.000000 | 58.5 | V | 13.8 | 15.5 | 74.0 |
| 16363.000000 | 58.4 | Н | 15.2 | 15.6 | 74.0 |
| 16625.000000 | 59.3 | Н | 15.1 | 14.7 | 74.0 |
| 17354.000000 | 59.1 | V | 15.5 | 14.9 | 74.0 |

Set.2 USB mode / Average detector

| Frequency(MHz) | Result(dBuV/m) | Polarity | A _{Rpl} (dB) | Margin(dB) | Limit (dBµV/m) |
|----------------|----------------|----------|-----------------------|------------|-------------------|
| 4.4404.000000 | 44.0 | 1.1 | 40.4 | 0.0 | |
| 14401.000000 | 44.8 | Н | 13.4 | 9.2 | 54.0 |
| 14974.000000 | 45.3 | Н | 13.8 | 8.7 | 54.0 |
| 15790.000000 | 47.2 | Н | 14.2 | 6.8 | 54.0 |
| 16298.000000 | 47.1 | Н | 14.9 | 6.9 | 54.0 |
| 16828.000000 | 47.7 | Н | 15.5 | 6.3 | 54.0 |
| 17419.000000 | 47.0 | Н | 15.6 | 7.0 | 54.0 |

Note: The measurement result of Set.1 and Set.2 showed here are worst cases of combinations of different batteries and USB cables.



Charging mode: Set 1

FCC-RE1-Part 15-30M-1G




Figure A.1 Radiated Emission from 30MHz to 1GHz

FCC-RE2-1-18G-PEAK+AV




Figure A.2 Radiated Emission from 1GHz to 18GHz



USB mode: Set 2

FCC-RE1-Part 15-30M-1G




Figure A.3 Radiated Emission from 30MHz to 1GHz






Figure A.4 Radiated Emission from 1GHz to 18GHz



A.2 Conducted Emission (§15.107(a))

Reference

FCC: CFR Part 15.107(a)

A.2.1 Method of measurement

For equipment that is designed to be connected to the public utility (AC) power line, the radio frequency voltage that is conducted back onto the AC power line on any frequency or frequencies within the band 150 kHz to 30 MHz shall not exceed the limits. Tested in accordance with the procedures of ANSI C63.4 - 2003, section 7.2.

A.2.2 EUT Operating Mode:

The MS is operating in the USB mode and charging mode. During the test MS is connected to a PC via a USB cable in the case of USB mode and is connected to a charger in the case of charging mode. The model of the PC is Lenovo Thinkcentre M4099t, and the serial number of the PC is SA08850737. The software is used to let the PC keep on copying data to MS, reading and erasing the data after copy action was finished.

A.2.3 Measurement Limit

| Frequency of emission (MHz) | Conducted limit (dBµV) | | | | |
|--|------------------------|-----------|--|--|--|
| | Quasi-peak | Average | | | |
| 0.15-0.5 | 66 to 56* | 56 to 46* | | | |
| 0.5-5 | 56 | 46 | | | |
| 5-30 | 60 | 50 | | | |
| *Decreases with the logarithm of the frequency | | | | | |

A.2.4 Test Condition in charging mode

| Voltage (V) | Frequency (Hz) |
|-------------|----------------|
| 120 | 60 |

| RBW | Sweep Time(s) |
|------|---------------|
| 9kHz | 1 |

CE Measurement uncertainty: 2.7 dB (K=2)



A.2.5 Measurement Results Charging mode:Set.1

ESH2-Z5 Scan-FCC




Figure A.5 Conducted Emission

Final Measurement Detector 1

| Frequency | QuasiPeak | DE | т. | Corr. | Margin | Limit |
|-----------|-----------|-----|------|-------|--------|---------|
| (MHz) | (dB µV) | PE | Line | (dB) | (dB) | (dB µV) |
| 0.166000 | 50.8 | FLO | L1 | 10.0 | 14.4 | 65.2 |
| 0.174000 | 49.8 | FLO | N | 10.1 | 14.9 | 64.8 |
| 0.182000 | 42.7 | FLO | N | 10.1 | 21.7 | 64.4 |
| 0.202000 | 47.4 | FLO | L1 | 10.0 | 16.2 | 63.5 |
| 0.210000 | 43.4 | FLO | N | 10.1 | 19.8 | 63.2 |
| 0.246000 | 39.9 | FLO | L1 | 10.0 | 22.0 | 61.9 |

Final Measurement Detector 2

| Frequency | Average | PE | Line | Corr. | Margin | Limit |
|-----------|--------------|-----|------|-------|--------|---------|
| (MHz) | $(dB \mu V)$ | PE | Line | (dB) | (dB) | (dB µV) |
| 2.550000 | 27.3 | FLO | L1 | 10.2 | 18.7 | 46.0 |
| 2.606000 | 27.8 | FLO | L1 | 10.2 | 18.2 | 46.0 |
| 2.646000 | 27.5 | FLO | L1 | 10.2 | 18.5 | 46.0 |
| 2.954000 | 25.9 | FLO | L1 | 10.1 | 20.1 | 46.0 |
| 3.134000 | 27.3 | FLO | L1 | 10.2 | 18.7 | 46.0 |
| 3.162000 | 26.9 | FLO | L1 | 10.2 | 19.1 | 46.0 |



USB mode:Set.2

ESH2-Z5 Scan-FCC




Figure A.6 Conducted Emission

Final Measurement Detector 1

| Frequency | QuasiPeak | PE | Lina | Corr. | Margin | Limit |
|-----------|-----------|-----|------|-------|--------|---------|
| (MHz) | (dB µV) | PE | Line | (dB) | (dB) | (dB µV) |
| 0.150000 | 44.0 | FLO | N | 10.1 | 22.0 | 66.0 |
| 0.162000 | 43.2 | FLO | N | 10.1 | 22.1 | 65.4 |
| 0.342000 | 30.8 | FLO | N | 10.0 | 28.3 | 59.2 |
| 0.374000 | 33.7 | FLO | L1 | 10.0 | 24.7 | 58.4 |
| 0.398000 | 33.8 | FLO | L1 | 10.0 | 24.1 | 57.9 |
| 9.538000 | 25.7 | FLO | N | 10.3 | 34.3 | 60.0 |

Final Measurement Detector 2

| mui vicusui ement Detector 2 | | | | | | |
|------------------------------|--------------|-----|------|-------|--------|--------------|
| Frequency | Average | PE | Line | Corr. | Margin | Limit |
| (MHz) | $(dB \mu V)$ | PE | Line | (dB) | (dB) | $(dB \mu V)$ |
| 8.546000 | 14.4 | FLO | L1 | 10.3 | 35.6 | 50.0 |
| 9.102000 | 15.0 | FLO | L1 | 10.3 | 35.0 | 50.0 |
| 9.322000 | 15.1 | FLO | L1 | 10.3 | 34.9 | 50.0 |
| 9.538000 | 16.3 | FLO | N | 10.3 | 33.7 | 50.0 |
| 9.754000 | 16.3 | FLO | N | 10.3 | 33.7 | 50.0 |
| 24.002000 | 34.3 | FLO | N | 10.6 | 15.7 | 50.0 |

END OF REPORT