

<div data-bbox="118 159 329 221"> <h1>HIBY R3II</h1> <p>用户指南 QUICK GUIDE</p> </div> <div data-bbox="152 372 292 391"> </div>	<div data-bbox="621 88 711 122"> <p>中文</p> </div> <div data-bbox="494 141 842 358"> <p>感谢您购买了HiBy推出的便携高清无损播放器R3II。</p> <p>为了让R3II给您带来更好的体验，这份说明书将介绍R3II的功能和使用方法，希望您更了解R3II,使用得更畅快。HiBy R3II是一款高性能、高保真的数字音频播放器，能支持DSD、DXD、WAV、FLAC、MQA、ALAC、APE、WMA无损/有损AIFF、AAC、MP3、MP2、OGG、Vorbis等多种无损/有损音乐格式。</p> </div>	<div data-bbox="935 54 1084 68"> <p>机器按键与接口介绍</p> </div> <div data-bbox="935 100 1258 417"> </div>	<div data-bbox="1379 58 1728 389"> <p>1.触摸控制，屏幕为3.2' IPS多点触摸屏，分辨率320*480；</p> <p>2.音量键+电源键：长按开关机，短按关闭屏幕，旋转调整音量</p> <p>3.RGB LED：会根据机器不同状态和当前歌曲采样率而变更颜色：          红色--充电          黄色--≤48K          青色--88.2K~192K          橙色--352.8K-以上          白色--DSD64~256          绿色--MQA          蓝色--MQA studio          洋红色--MQA Rendering</p> </div>	<div data-bbox="1824 58 2172 389"> <p>1.Micro SD卡，R3II以外置Micro SD储存曲目，Micro SD支持最大2TB。Micro SD卡安装在R3II内，而R3II以提供的USB线连上电脑时，在电脑上可看见该卡并将歌曲拖拉进去以拷贝歌曲。拔掉USB线前请在电脑中将卡“安全退出”。</p> <p>2.Type C接口，数据传输+充电+同轴输出，同轴输出需要用专用的Type C转3.5mm同轴线，可到官方京东商城HiBy数码旗舰店选购。</p> <p>6.3.5mm耳机口：CITA美标，支持线控</p> <p><b>海贝音乐APP</b>          R3II配合海贝音乐APP使用体验更佳，支持WiFi传歌，把手机、电脑、平板歌曲通过同一</p> </div>	<div data-bbox="2265 54 2613 362"> <p>WiFi传送到R3II上；HiByLink遥控功能，通过手机蓝牙连接并控制R3II，可从手机端切歌、选歌、管理歌单，扫码下载海贝音乐APP。</p> <p><b>USB DAC</b>          1.请前往www.hiby.com官网下载相应驱动并仔细阅读相关说明；          2.R3II作为USB DAC，需要在系统设置---USB模式---选择音频，并用数据线 with 电脑相连。</p> </div>	<div data-bbox="2713 58 3061 344"> <p><b>传送门功能</b>          1.R3II作为蓝牙声卡，USB→R3II→蓝牙耳机，R3II作为电脑DAC同时可使用蓝牙耳机/音箱收听音乐，支持LDAC 96kHz，最高支持UAT 192kHz；          2.R3II作为蓝牙转盘，通过手机与R3II蓝牙连接，R3II可以通过USB成为一个高品质的蓝牙转盘，支持同轴输出、USB Audio out，或作为底座，支持LDAC 96kHz，最高支持UAT 192kHz。          3.R3II作为无线转盘，安卓系统使用DLNA(网易云等APP)、iOS系统使用AirPlay，连接R3II，R3II可以通过USB成为一个无线转盘，支持同轴输出、USB Audio out，或作为底座。</p> </div>
<div data-bbox="55 501 404 840"> <p><b>无线功能</b>          1.WiFi，支持2.4G WiFi，支持WiFi传歌、HiByLink（需要海贝音乐APP）、DLNA、AirPlay、OTA在线更新、网络收音机、流媒体Tidal和Qobuz（系统语言非简体下出现）；</p> <p>2.蓝牙，支持蓝牙5.1，支持多种蓝牙高清协议UAT、LDAC、aptX等。</p> <p><b>固件升级</b>          1.OTA在线升级，在无线设置中打开WiFi，并连接WiFi，然后到系统设置---系统升级---网络升级即可升级最新固件；</p> <p>2.MircoSD卡更新，请前往www.hiby.com官网下载相应固件，并导入MircoSD卡，把卡插入机器内，进入系统设置---系统升级---MircoSD卡升级，即可升级最新固件。</p> </div>	<div data-bbox="506 501 832 639"> <p>更多操作说明请扫描二维码并在“HiBy音乐”公众号回复“R3II说明书”</p> </div>	<div data-bbox="1034 491 1184 526"> <p>ENGLISH</p> </div> <div data-bbox="935 542 1283 810"> <p>Thank you for purchasing the portable digital audio player HiBy R3II. To help you get the best out of the R3II, this user guide has been compiled to introduce you to the R3II's features and how to use them. Please read thoroughly in the first days of ownership.</p> <p>The HiBy R3II is a high performance, high fidelity digital audio player that supports DSD, DXD, WAV, FLAC, MQA, ALAC, APE, WMA lossless/lossy, AIFF, AAC, MP3, MP2, Ogg Vorbis and other lossless/lossy music formats.</p> </div>	<div data-bbox="1395 473 1712 868"> <p><b>Buttons and ports</b></p> </div>	<div data-bbox="1824 501 2172 836"> <p><b>Buttons and ports</b>  <b>Touch control:</b> The screen is an IPS multi-touch touchscreen, with 3.2' size and 320*480 resolution;</p> <p><b>Power button + Volum knob</b> : Long press to power on/off, short press to lock screen, rotate to adjust volume;</p> <p><b>Multicolor LED:</b> Changes colors depending on what is playing in terms of sample rate:          Red: Charging          Yellow: ≤48k          Aqua: 88.2k~192k          Orange: ≥352.8k</p> </div>	<div data-bbox="2265 501 2613 836"> <p>White: DSD64~256          Green: MQA          Blue: MQA studio          Magenta: MQA rendering</p> <p><b>Micro SD card:</b> The R3II carries an external Micro SD slot for music storage, supporting Micro SD cards up to ≤2TB. When putting in a Micro SD card for the first time or changing cards, you need to scan for new songs. Connected to the computer via the supplied USB cable, the R3II can act as a card reader for transferring music onto the micro SD card inserted into the R3II. After transferring songs please "safely eject" the card in the</p> </div>	<div data-bbox="2713 501 3061 792"> <p>computer before unplugging the USB cable.</p> <p><b>USB Type C port:</b> for data transmission + charging + coaxial digital output. A special Type C to 3.5mm coaxial cable is required for using the coaxial digital output. It can be purchased from store.hiby.com or your local dealer. Please note that this special cable only works with the R3II.</p> <p><b>3.5mm headphone port:</b> For CTIA-standard headsets. Inline remote is supported.</p> </div>

TEL: 0086-769-23182216 Website: [www.hiby.com](http://www.hiby.com)  
Email: [service@hiby.com](mailto:service@hiby.com)  
Address: Room 1201, Lianjing Commercial Building, No.39,  
Hongwei 3rd Road, Nancheng District, Dongguan,  
Guangdong, China