

Product Report Card

Manufacturer: GE Lighting Solutions

Model Number 93131045

Tested:

Other Model LED3DBC/DLGC15, 93131046, LED3DBC/SWGC15, 93131047, LED3DCAC/DLGC15,

Numbers: 93131048, LED3DCAC/SWGC15

Manufacturer's Description

Type of Device: LED 3 W Candle

Operating Voltage: 120

Input Power: 3 W

Input Current: 0.035 A

Input Frequency: 60 Hz

Control Type: Forward and Reverse Phase Control

Dimming Range: Not Specified

Output Power: Not Specified

Lumen Output: 300 lm

Type/Shape: Candle

Base Type: E12

Lutron Test Results

Date Tested 06/02/2023

Test Voltage 120 V

Test Notes Test results valid only at 120V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
Commercial Systems							
Vive	MRF2S-6ELV	RP	1 - 50	1%	100%	12%	
Vive	MRF2S-6CL	FP	1 - 50	3%	100%	16%	
Vive	MRF2S-6ND	FP	1 - 50	3%	100%	16%	
Panel Module	GP (Harrier) Card	FP	1 - 215	1%	100%	10%	Rating is per output. Use load type 2-1.
Grafik QS/Wallbox Power Module	Grafik Eye QS Main Unit Family/LQRJ-WPM-6P	FP	1 - 215	1%	100%	10%	Rating is per channel; total quantity per Main Unit is 537.
Grafik Eye 3000/HomeWorks Illumination/HomeWorks QS	Grafik Eye 3000 Family/HWI-WPM-6D-120	FP	1 - 215	1%	100%	10%	
Energi Savr Node DIN-Rail (120/277 V PRO LED+ Phase Adaptive)	QSN-4A5-S (Zones 2-4 - Reverse-Phase)	RP	1 - 128	1%	100%	10%	

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
Energi Savr Node DIN-Rail (120/277 V PRO LED+ Phase Adaptive)	QSN-4A5-S (Zone 1 - Reverse-Phase)	RP	1 - 190	1%	100%	10%	
Energi Savr Node DIN-Rail (120/277 V PRO LED+ Phase Adaptive)	QSN-4A5-S (Zones 2-4 - Forward-Phase)	FP	1 - 47	1%	100%	10%	
Energi Savr Node DIN-Rail (120/277 V PRO LED+ Phase Adaptive)	QSN-4A5-S (Zone 1 - Forward-Phase)	FP	1 - 62	1%	100%	10%	

Interfaces

No applicable results

Residential Systems

Caseta Wireless	PD-6WCL (SD12)	FP	1 - 50	3%	100%	16%	
RA2 Select/RadioRA 2/RadioRA 3	RRD-PRO, RP, w/ neutral (default)	RP	1 - 83	1%	100%	12%	
HomeWorks QS/HomeWorks QSX	HQRx-PRO, RP, w/ neutral (default)	RP	1 - 83	1%	100%	12%	
RadioRA 3	RRST-PRO-N, RP	RP	1 - 83	1%	100%	12%	
HomeWorks QSX	HRST-PRO-N, RP	RP	1 - 83	1%	100%	12%	
Caseta WirelessPhase Selectable	PD-5NE	RP	1 - 83	1%	100%	12%	
RA2 Select/RadioRA 2/RadioRA 3	RRD-10ND	FP	1 - 50	3%	100%	16%	
HomeWorks QS/HomeWorks QSX	HQRD-6ND	FP	1 - 50	3%	100%	16%	
HomeWorks	HxD-6ND	FP	1 - 50	3%	100%	16%	
HomeWorks QS/HomeWorks QSX	HQRD-10ND	FP	1 - 50	3%	100%	16%	
Caseta Wireless	DVRF-6L (Vogelkop)	FP	1 - 50	3%	100%	16%	
RadioRA 2/RadioRA 3	Hybrid Keypad LED+ RRD-HN6BRL	FP	1 - 33	3%	100%	16%	Installation with a neutral wire is required.
HomeWorks QS/HomeWorks QSX	Hybrid Keypad LED+ HQRD-HN6BRL	FP	1 - 33	3%	100%	16%	Installation with a neutral wire is required.
Panel Module	GP (Harrier) Card	FP	1 - 215	1%	100%	10%	Rating is per output. Use load type 2-1.
Grafik QS/Wallbox Power Module	Grafik Eye QS Main Unit Family/LQRJ-WPM-6P	FP	1 - 215	1%	100%	10%	Rating is per channel; total quantity per Main Unit is 537.
Grafik Eye 3000/HomeWorks Illumination/HomeWorks QS	Grafik Eye 3000 Family/HWI-WPM-6D-120	FP	1 - 215	1%	100%	10%	
HomeWorks QS/HomeWorks QSX DIN-Rail Power Module (120/277 V PRO LED+ Phase Adaptive)	LQSE-4A5-120-D (Zones 2-4 - Reverse-Phase)	RP	1 - 128	1%	100%	10%	
HomeWorks QS/HomeWorks QSX DIN-Rail Power Module (120/277 V PRO LED+ Phase Adaptive)	LQSE-4A5-120-D (Zone 1 - Reverse-Phase)	RP	1 - 190	1%	100%	10%	

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.

This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.
