

PAR LED BULB Dimmer Compatibility Guide

Sunco Lighting Inc. ("Sunco") compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.



Brand	Model	PAR20	PAR30	PAR38	Brand	Model	PAR20	PAR30	PAR38
AH	SDM/600/White 600W	✓	✗	✗	Leviton	Light Almond No.6681 600W	✗	✓	✓
	SDM3/1000/White 1000W	✓	✓	✓		S-600P-WH	✗	✓	✓
Cooper	DAL06P-C2-K	✗	✗	✗		White No.6631 600W	✓	✓	✓
	SAL06P-W-K	✗	✗	✗		White No.6674 600W	✗	✓	✓
	TAL06P-C2-K	✗	✗	✗		White No.IPL06 600W	✓	✓	✓
CTL	DM600-12-3 600W	✓	✓	✓		White/Ivory/Light Almond IPI10-1LZ 600W	✗	✗	✗
Eaton	AAL06-C1	✗	✗	✗		6631-LA 600W	✓	✓	✓
	TAL06P1-C5	✗	✗	✗	Lutron	AY-600PH-WH	✗	✗	✗
GE	18024 600W	✗	✗	✗		AYCL-153PH	✓	✓	✓
Halo	SAL06P-W-HALOGF2	✗	✗	✗		AYCL-153P-WH	✓	✓	✓
Legrand	HCL453PTC	✓	✗	✗		CT-103P-WH 1000W	✓	✓	✓
	RHCL453PW	✓	✓	✓		CT-600PR-WH 600W	✗	✓	✓
Leviton	603-6631-A 600W	✓	✗	✗		CTCL-153PDH-WH	✓	✓	✓
	6631-A 600W	✓	✓	✓		CTCL-153PDH-WH	✓	✓	✓
	6681	✓	✓	✓		CTCL-153P-WH 600W	✗	✓	✓
	6683-10Z 600W	✓	✓	✓		D-600PH-DK 600W	✓	✗	✗
	6684 600W	✓	✓	✓		D-600RH-DK 600W	✓	✗	✗
	Almond LUXDM600-12 600W	✓	✓	✓		D-600R-IV 600W	✓	✗	✗
	IPI06 600W	✓	✓	✓		D-600R-WH 600W	✓	✓	✓
	IPI06-1LZ 600W	✓	✓	✓		DV-600PH-WH 600W	✓	✓	✓
	Light Almond No.6672 600W	✓	✓	✓					

Continued...

We highly recommend using an LED dimmer that is also an ELV (electronic low voltage) dimmer. A buzzing or flickering light is typically an indication that the dimmer being used is not compatible with the lights. Please consult dimmer manufacturer for maximum lamps per dimmer capacity.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.



PAR LED BULB Dimmer Compatibility Guide

Sunco Lighting Inc. ("Sunco") compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.



Brand	Model	PAR20	PAR30	PAR38	Brand	Model	PAR20	PAR30	PAR38
Lutron	DV-600P-WH	✗	✓	✓	Lutron	MAW-600H-WH 600W	✓	✓	✓
	DV-603P600W	✗	✓	✓		MSCL-OP153MH-WH	✓	✓	✓
	DV-603PH-WH 600W	✓	✗	✗		PD-6WCL-WH-P	✗	✓	✓
	DV-603PH-WH 600W	✓	✓	✓		S-10PH 1000W	✓	✗	✗
	DV-603PR 600W	✗	✓	✓		S-600 600W	✓	✗	✗
	DVCL-153PH 600W	✗	✓	✓		S-600-AL 600W	✓	✗	✗
	DVCL-153P-WH	✓	✓	✓		S-600H-WH 600W	✓	✗	✗
	DVCL-153P-WH 600W	✗	✓	✓		S-600-IV 600W	✓	✗	✗
	DVCL-153P-WH-3	✓	✓	✓		S-600PR-WH 600W	✗	✓	✓
	DVCL-253PH	✓	✓	✓		S-600P-WH	✗	✓	✓
	DVW-600PH-WH 600W	✗	✓	✓		S-603PGH-WH 600W	✗	✗	✗
	DVWCL-153PH-WH 600W	✗	✓	✓		S-603PH-WH 600W	✗	✓	✓
	DVWCL-153PH-WHC	✗	✓	✓		SCL-153P-WH 600W	✗	✓	✓
	LECL-153PH-WH	✓	✗	✗		TG-600PH-IV 600W	✓	✓	✓
	MACL-153MH-WH	✓	✓	✓		TG-600PH-WH 600W	✗	✓	✓
	MACL-153MLH-WH	✓	✓	✓		TG-600PNLH-WH	✗	✗	✗
	MACL-153MLRHW-WH	✓	✓	✓		TG-603PGH-WH	✗	✗	✗
	MACL-153MR-WH	✓	✓	✓		TGCL-153PH-WH	✓	✓	✓
	MACL-153M-WH	✓	✓	✓		TGCL-153PLH-WH 600W	✓	✓	✓
	MAELV-600-WH	✓	✓	✓		TGCL-153PH-WH 600W	✓	✓	✓
	MAW-600H-AL 600W	✓	✓	✓					

We highly recommend using an LED dimmer that is also an ELV (electronic low voltage) dimmer. A buzzing or flickering light is typically an indication that the dimmer being used is not compatible with the lights. Please consult dimmer manufacturer for maximum lamps per dimmer capacity.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

