HP LaserJet Pro 3001dwe Wireless Black & White Printer with HP+



Powerful productivity. Seamless management.

Get fast printing speeds and smart capabilities for effortless, secure, and sustainable printing.

This HP+ laser printer is built with powerful productivity features for small teams — fast speeds, advanced security, and smart office features so you can setup and manage it from anywhere.



This is an HP+ printer. It requires an HP account, connection to the internet, and exclusive use of Original HP Toner cartridges for the life of the printer. More at: http://www.hp.com/plus-faq

Print Speed: Letter: Up to 35 ppm black; First Page Out: As fast as 6.6 sec black

Print Resolution: Black (best): Up to 1200 x 1200 dpi **Standard Connectivity:** Hi-Speed USB device (compatible with USB 2.0 specifications); 10/100Mbps Ethernet; Wireless 802.11b/g/n, Dual band 2.4GHz/5GHz; BLE.

Mobile Printing Capability: HP Smart App; Apple AirPrint™; Wi-Fi® Direct printing; HP ROAM For Business; Optional ROAM Queue Printing

Duty cycle: Monthly (letter): Up to 50,000

Paper Handling: 1 main tray; 250 sheets or 10 envelopes; 150 sheets output tray













Powerful productivity.

- Support your small workteams with this smart printer, designed for up to 7 users.
- Print more efficiently. Save time, paper, and costs with fast speeds and auto two-sided printing.
- Do more in fewer steps. Simple shortcuts allow your employees to complete common tasks with just a touch.
- Get productivity in the palm of your hand. Optimize print tasks and time with Shortcuts from the HP Smart app.

Effortless management.

- Guided, cloud-based setup makes it easy to configure new printers and onboard users from any location.²
- Smart Admin Dashboard monitors usage and controls settings across multiple printers, in multiple locations.²
- Seamless connectivity allows you to print from anywhere, any device, on any network. ^{1,3}
- Dedicated tech support can help you when you need it, all backed by our 2-year extended HP warranty.^{4,5}

HP Wolf Pro Security, made better with HP+.

- Get printer security out of the box. Preconfigured settings mean it's ready when you are.
- Set up your printer security from the dashboard. Smart Admin makes IT configuration and monitoring easy.²
- Automated 24/7 monitoring helps ensure your printers and your information are always secure.
- Add a layer of security. PIN/pull option authenticates your print jobs only when you're present.

Hassle-free supplies management with Instant Ink for lasers.

- Enroll to save on Original HP Toner with Instant Ink. Get toner, delivery, and recycling. 8,9,10
- Never run out of toner with Instant Ink for lasers.¹¹ Cartridges are delivered automatically and only when you need it.
- Manage your subscription to get cartridges delivered to multiple locations on a single consolidated bill.⁹
- With Instant Ink, you get to select the right plans for each of your printers. Change or cancel at any time.

HP LaserJet Pro 3001dwe Wireless Black & White Printer with HP+ Technical specifications

Functions	Print
Print speed black	Letter: Up to 35 ppm; First page out: As fast as 6.6 sec; Print speed duplex: Up to 21 ipm
Print resolution	Black (best): Up to 1200×1200 dpi; Black (fine lines): Up to 1200×1200 dpi
Print technology	Laser
Print resolution technologies	600dpi with Resolution Enhancement technology (REt); HP ProRes 1200
Print cartridges number	1 (black)
Standard print languages	PCL5c; PCL6; PS; PCLmS; PDF; URF; PWG; PCLm
Printer smart software features	Automatic duplex, Easy OOBE, Shortcut by admin, Smart security, HP Smart Pro, Print always work, Print anywhere, HP Smart Admin
Standard connectivity	Hi-Speed USB device (compatible with USB 2.0 specifications); 10/100Mbps Ethernet; Wireless $802.11b/g/n$, Dual band $2.4GHz/5GHz$; BLE.
Network capabilities	10/100Mbps Ethernet; Wireless 802.11b/g/n, Dual band 2.4GHz/5GHz.
Wireless capability	Yes
Mobile printing capability	HP Smart App; Apple AirPrint TM ; Wi-Fi® Direct printing; HP ROAM For Business; Optional ROAM Queue Printing
Memory	Standard: 256 MB; Maximum: 256 MB
Processor speed	800 MHz
Duty cycle	Monthly letter: Up to 50,000
Recommended monthly page volume	350 to 2500 pages
Media types supported	Paper (Cut sheets, plain, glossy film, labels), envelopes, card stock, postcards
Media weight supported	16 to 43 lb
Media sizes supported	Letter; Legal; Executive; Oficio 8.5x13; 3x5; 4x6; 5x7; 5x8; Envelope #10; Envelope Monarch
Media Sizes Custom	Width 3 x 8.5 in ; Length 5 to 14 in
Paper handling	Input Capacities: Up to 250 sheets Standard Output Capacities: Up to 150 sheets Standard Duplex Options: Automatic (standard) Envelope feeder: No Standard paper trays: 1

	•
What's in the box	3G650E HP LaserJet Pro 3001dwe Printer, HP Black LaserJet Toner Introductory Cartridge, yield ~1000 pages, Setup Guide, Reference Guide, Regulatory Flyer, HP+ Concierge Support Flyer, Warranty Guide, Power cord
Replacement cartridges ³	HP 138A Original Black Laser Jet Toner Cartridge (~1,500 yield) W1380A HP 138X Original Black Laser Jet Toner Cartridge (~4,000 yield) W1380X
Product dimensions	W x d x h: 14.4 x 15.7 x 8.6 in; Maximum: 14.4 x 29.9 x 14.4 in
Product weight	16.1lb
Warranty features	Two-year limited warranty
Energy efficiency compliance	ENERGY STAR® certified
Energy star certified	Yes
Blue Angel Compliance	No
Sustainable impact specifications	Mercury free
Control panel	4 Buttons (ON, Wireless, Info, Cancel/Resume); 3 Indicator LEDs (Paper, Attention, Toner).
Software included	No CD inbox (except Indonesia and China Gov) Downloadable Software from hp.com, hpsmart.com/setup, in-OS app stores. #CD include HP Software Installer, Uninstaller, printer driver and other essential tools
Compatible operating systems	Microsoft® Windows® 11, 10: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, Microsoft® Internet Explorer (Windows 10 or below) or Edge (Win11). Apple® macOS v10.15 Catalina, macOS v11 Big Sur, macOS v12 Monterey.; 2 GB HD; Internet required; Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Compatible network operating systems	Windows Server 2008 R2 64-bit, Windows Server 2008 R2 64-bit (SP1), Windows Server 2012 64-bit, Windows Server 2012 R2 64-bit, Windows Server 2016 64-bit, Linux- For more information see http://developers.hp.com/hp-linux-imaging-and-printing,
Minimum system requirements	PC: Microsoft® Windows® 11, 10: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection.; Mac: Apple® macOS v10.15 Catalina, macOS v11 Big Sur, macOS v12 Monterey; 2 GB HD; Internet required
Power	Power supply type: Internal (built-in) Power Supply; Power requirements: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz/50 Hz; 220-volt input voltage: 220 to 240 VAC (+/- 10%), 60 Hz/50 Hz; Power consumption: 484 watts (active printing), 2.93 watts (ready), 1.06 watts (sleep), 0.06 watts(Manual Off), 0.06 watts (Auto Off/Manual On), 0.9watts (Auto Off/Wake on LAN)
Acoustics	Acoustic power emissions: 6.5 B(A) (printing at 33ppm)
Operating environment	Operating temperature range: 59 to 90.5°F; Recommended operating temperature: 63.5 to 77°F; Storage temperature range: -4 to 140°F; Operating humidity range: 10 to 80% RH; Recommended humidity operating range: 30 to 70% RH
HP Service and Support options	U13F9E - HP Plus 3y Std Exch LJ Mid SVC; U13FCE - HP Plus 3y NBD Exch LJ Mid SVC; U13FDE - HP Plus 4y NBD Exch LJ Mid SVC; U16FVE - HP Plus 3y Onsite Exch LJ Mid SVC; U16FWE - HP Plus 4y Onsite Exch LJ Mid SVC; U16FYE - HP Plus 3y Return to Depot LJ Mid SVC; U16FYE - HP Plus 4y Return to Depot LJ Mid SVC; U16G0PE - HP Plus 1y PW NBD Exch LJ Mid SVC; U16G1PE - HP Plus 1y PW Onsite Exch LJ Mid SVC; U16G2PE - HP Plus 1y PW Return to Depot LJ Mid SVC

Learn more at hp.com

¹ For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. ² Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115V device. ³ Declared yields based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/toneryield ⁴ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ⁵ Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ⁵ Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

