

Serie | 6, Domino electric hob, 30 cm, Black PKF375FP2E







Optional accessories

 ${\sf HEZ394301}: Connecting\ strip$

Ceramic domino hob: tough and easy-toclean glass surfaces and good looks for a smart addition to your home.

- **DirectSelect:** Direct, simple selection of the desired cooking zone, power and additional functions.
- The 18 cm cooking zone extendable cooking zone.
- ComfortProfil: Elegant, appealing design with bevelled front and metal strips on the side.
- 30 cm width: suitable for combining with other Domino and ComfortProfile hobs.
- PowerBoost: up to 20% more energy when cooking on your electric hob.

Technical Data

Product name/family: Vario/Domino cooking zone cera

Construction type : Built-in Energy input : Electric

Total number of positions that can be used at the same time : $\ensuremath{\mathbf{2}}$

Required niche size for installation (HxWxD) : 38 x x mm

Width of the appliance : 306 mm Dimensions : 38 x 306 x 527 mm

Dimensions of the packed product (HxWxD) : 120 x 380 x 590

 $\mathsf{m}\mathsf{m}$

Net weight : 4.5 kg Gross weight : 5.2 kg

Residual heat indicator: Separate Location of control panel: Hob front Basic surface material: Ceramic Color of surface: Alu, brushed, Black Approval certificates: AENOR, CE Length of electrical supply cord: 100 cm

EAN code: 4242005283286

Electrical connection rating : 3500 \mbox{W}

Fuse protection : 16 A Voltage : 220-240 V Frequency : 50; 60 Hz





Serie | 6, Domino electric hob, 30 cm, Black PKF375FP2E

Ceramic domino hob: tough and easy-toclean glass surfaces and good looks for a smart addition to your home.

Flexibility of cooking zones

- Ring zone double: use regular or larger cookware on the extendable cooking zone.
- Cooking zone middle: 120 mm, 180 mm, 1 KW (max. power 2.3 KW)
- Cooking zone middle: 145 mm, 1.2 KW

Usage convenience

- DirectSelect touch control: directly control the power with imprinted touch bar.
- Variable 17-stage power settings for each zone: precisely adapt the heat with 17 power levels (9 main levels and 8 intermediate levels).
- Timer for all zones
- : switches off the cooking zone at the end of the time set (e.g. for boiled eggs).
- Timer shows how long the cooktop is in use : an alarm sounds at the end of the time set (e.g. for pasta).
- Count up timer per cooktop
- : shows how much time has passed since starting the timer (e.g. for potatoes).

Time saving & efficiency

- PowerBoost in the front zone: boil water more quickly thanks to 20% more energy than at the highest standard level.
- ReStart function: in case of unintentional switch-off, this feature restores all previous settings by switching on the hob again within 4 seconds.

Design

- 30 cm: space for 2 pots or pans.
- Profile trim (front facette with side trim)

Safety

- 2 stage residual heat indicator for each zone: indicates which cooking zones are still hot or warm.
- Control panel lock: prevent unintended activation of the hob.
- Main on/off switch: switch off all cooking zones at the touch of a button.
- Power on indicator light: indicates if the hob is heating.
- Automatic safety shut off: for safety reasons, heating stops after a preset time if not used (possible to customise).
- Energy consumption display: shows the electricity consumption of the last cooking process.

Installation


- Dimensions of the product (HxWxD mm): 38 x 306 x 527
- Required niche size for installation (HxWxD mm) : 38 x 270 x (490 500)
- Min. worktop thickness: 16 mm
- Connected load: 3.5 KW
- Power cord: 1 m, Cable included



Serie | 6, Domino electric hob, 30 cm, Black PKF375FP2E



measurements in mm




When installing a Domino unit right next to a hob, an assembly kit (HEZ394301) is required.

measurements in mm Domino combination options with corresponding appliance and cut-out dimensions

Width category: Appliance width:


ABCDLX						
2x30	306	306	-	-	612	576
1x30, 1x40	306	396	-	-	702	666
1x30, 1x60	306	606	-	-	912	876
1x30, 1x70*	306	710	-	-	1016	980
1x30, 1x80	306	816	-	-	1122	1086
1x30, 1x90	306	916	-	-	1222	1186
2x40	396	396	-	-	792	756
1x40, 1x60	396	606	-	-	1002	966
1x40, 1x70*	396	710	-	-	1106	1070
1x40, 1x80	396	816	-	-	1212	1176
1x40, 1x90	396	916	-	-	1312	1276
3x30	306	306	306	-	918	882
2x30, 1x40	306	306	396	-	1008	972
2x30, 1x60	306	306	606	-	1218	1182
2x30, 1x70*	306	306	710	-	1322	1286
2x30, 1x80	306	306	816	-	1428	1392
2x30, 1x90	306	306	916	-	1528	1492
1x30, 2x40	306	396	396	-	1098	1062
1x30, 1x40, 1x60	306	396	606	-	1308	1272
1x30, 1x40, 1x70*		396	710	-	1412	1376
1x30, 1x40, 1x80	306	396	816	-	1518	1482
1x30, 1x40, 1x90	306	396	916	-	1618	1582
2x40, 1x60	396	396	606	-	1398	1362
4×30	1306	306	306	306	1224	1188

measurements in mm Assembly kit (HEZ394301) for Domino




B: Dependent on the cut-out depth

measurements in mm



When installing two or more Domino units side-by-side, one or more assembly kits are required (2 units = 1 assembly kit, 3 units = 2 assembly kits, etc.).

measurements in mm




- A: Minimum distance from the hob cut-out
- to the wall.

 B: Recessed depth


 C: With fitted oven underneath min. 20, possibly more; see space requirements for the oven.



Serie | 6, Domino electric hob, 30 cm, Black PKF375FP2E



When installing two Domino units right next to a hob, two assembly kits (HEZ394301) are required.



When installing two or more Domino units side-by-side, one or more assembly kits are required (2 units = 1 assembly kit, 3 units = 2 assembly kits, etc.).